



COIN MECHANISMS INC.

Model 3380 MDB Coin Changer Housing



Features & Benefits:

- Attach to your single vend device for a completely self-contained, locking money collection & vending control system
- Housing is made of .060 thick pre-galvanized CRS & powder coated in a black finish
- Equipped with either a Conlux 5 tube or a CoinCo 3 tube coin changer
- User controlled, dip-switch configurable MDB protocol PCB allows for flexibility of price settings and other unique options including: "free vend" capability, token supported, disable coins by denomination
- Standard vend price settings are in 5 cent increments up to \$3.15 (option for higher vend price settings also available)
- Accepts both U.S. & Canadian .05¢, .10¢, .25¢, \$1 plus the Canadian \$2
- 3-Digit LED displays both Price and Status Messages (including Error Codes)
- Brushed stainless steel coin entry assembly
- Integrated removable metal cashbox holds approximately 660 coins
- Conlux changer holds a maximum of \$66.15 in change (1 nickel tube, 1 dime tube, 3 quarter tubes) or expand to \$111.40 in change by exchanging one quarter tube for a \$1 tube

Specifications

- Box dimensions: 19-1/2" H x 10-1/4" W x 4-1/2" D
- Operating Voltage Range ~ 90 to 264V AC
- Built-In dual output 65W 24V/5V enclosed universal power supply
- AC input power supply and cable connections
- Indoor environmental operating spec. ~ 0 to 140° F



Coin Mechanisms Inc.
400 Regency Drive, P.O. Box 5128
Glendale Heights, IL 60139
Tel. 630.924.7070 Fax. 630.924.7088
Toll Free: 800.323.6498
e-mail: coinmech@coinmech.com
Website: www.coinmech.com

Canadian Sales Office:

Les Agences TLS Inc.
Brossard
Quebec
Tel. 450.444.0080
Fax. 450.444.4844
e-mail: claude@tlsinc.ca
Website: www.tlsinc.ca